

ISRO

**Previous Year Paper
Refrigeration and Air
Conditioning 2020**






GOVERNMENT OF INDIA : : DEPARTMENT OF SPACE
INDIAN SPACE RESEARCH ORGANISATION
ISRO Centralised Recruitment Board
Recruitment for Scientist/Engineer 'SC'

Test Booklet		MECHANICAL	A
Date	:	January 12, 2020 (Sunday)	
Time	:	1530 hrs to 1700 hrs	
Test Duration (Minutes)	:	90	
No. of Questions	:	80	
No. of Pages (Other than cover sheet)	:	16	

Instructions to the candidates

1. The question paper is in the form of test booklet. All candidates will be assessed on identical questions.
2. A separate OMR answer sheet is provided to all candidates for answering.
3. Each objective question is provided with a text and/or figures wherever applicable with **multiple answer choices (a), (b), (c) and (d)**. Choose the most appropriate answer.
4. Read the instructions on the OMR sheet carefully. Use only **Black or Blue Ball Point Pen** for writing on OMR sheet and marking/bubbling your answers.
5. All objective type questions carry equal marks of **THREE** for a correct answer, **ZERO** for no answer and minus **ONE** for a wrong answer.
6. **Multiple answers** for a question will be regarded as a wrong answer.
7. Although the test stresses on accuracy more than speed, it is important to use time as effectively as possible.
8. Do not spend time on questions, which are difficult for you. Go on to other questions and come back to the difficult ones later.
9. Question booklets have been marked with **A** or **B** or **C** or **D** or **E** on the right hand top corner, which is mandatory to be written on the OMR sheet in the box and bubbled appropriately, failing which, the answer sheet will not be evaluated.
10. Space available in the booklet could be used for rough work, if required. No separate sheet will be provided.
11. Attempt of any malpractice in the exam hall shall entail disqualification of candidature, debar from future exams and legal action against the candidate.

SEAL

	INDIAN SPACE RESEARCH ORGANISATION	SET A
	MECHANICAL	

1. A centrifugal pump having an impeller diameter of 127 mm, delivers a power of 12 hp. If the impeller diameter is changed to 254 mm, what is the power, if other parameters are kept constant?

(a) 48 hp	(b) 192 hp
(c) 24 hp	(d) 96 hp

2. In a circular tube of diameter 100 mm and length 13 m with laminar flow, the friction factor is estimated to be 0.05. Calculate the Reynolds number?

(a) 950	(b) 2300
(c) 1280	(d) None of the above

3. An open tank is filled with water to a height of 20m. What is the velocity of the water flow at the outlet, if the outlet is at the base of the tank?

(a) 40 m/s (approx.)	(b) 20 m/s (approx.)
(c) 10 m/s (approx.)	(d) 5 m/s (approx.)

4. For a non-dimensional specific speed value of 1, for maximum efficiency, which of the following turbines is preferred?

(a) Pelton wheel	(b) Francis turbine
(c) Kaplan turbine	(d) Tyson wheel

5. An experiment is conducted with a fluid of density 1 kg/m^3 at 10 m/s velocity. The free stream static pressure is 100 kPa and the local static pressure is 101 kPa. What is the pressure coefficient at the location?


(a) 70	(b) 80
(c) 20	(d) 50

6. In a P-V diagram of a steady flow compressor, the intercooling can be represented as

(a) Vertical line	(b) Horizontal line
(c) Parabolic line	(d) None of the above



7. Which of the following is a non-Newtonian fluid?
- (a) Air (b) Water
(c) Gasoline (d) None of the above
8. A hot body at 1000 K transfers 2000 kJ of heat to a body at 500 K. Determine the net entropy change?
- (a) +4 kJ/kg (b) -2 kJ/kg
(c) +2 kJ/kg (d) -4 kJ/kg
9. Highest ratio of specific heat is possible for?
- (a) Argon (b) Helium
(c) Hydrogen (d) Air
10. Which of the following can be used to determine the variation of saturation pressure with temperature along phase boundaries?
- (a) Joule-Thomson relation (b) Carnot equation
(c) Rankine-Hougoniot's relation (d) Clausius-Clapeyron relation
11. Air at 27 °C and 100 kPa enters in a steady flow to a nozzle at a velocity of 100 m/s. If the inlet area of the nozzle is 0.5 m², what is the mass flow rate through the system?
- (a) 116 kg/s (b) 232 kg/s
(c) 58 kg/s (d) 143 kg/s
12. Critical point of water is
- (a) 22.06 kPa (b) 22.06 MPa
(c) 22.06 atm (d) 22.06 mbar

	INDIAN SPACE RESEARCH ORGANISATION	SET A
	MECHANICAL	


13. In a shower mixer, cold water at 27 deg C, flowing at 5 kg/min is mixed with hot water at 77 deg C flowing at 15 kg/min. The exit temperature of the mixture is
- (a) 45.4 deg C (b) 64.5 deg C
(c) 34.5 deg C (d) 68.4 deg C
14. Which of the following uses a regenerator?
- (a) Brayton cycle (b) Ericsson cycle
(c) Stirling Cycle (d) Both (b) and (c)
15. Ratio of convective mass transfer to the mass diffusion rate is called?
- (a) Sherwood number (b) Schmidt number
(c) Rayleigh number (d) Strouhal number
16. A gas is contained in a cylinder with a moveable piston of 100 kg mass. When 2500 J of heat flows into the gas, the internal energy of the gas increases by 1500 J. What is the distance through which the piston rises?
- (a) 2 m (b) 1 m
(c) 2.5 m (d) 0.5 m
17. A refrigerator with COP of 5 is used in a room at 300 K. What will be the heat intake through a section of refrigerator wall of area 100 cm × 100 cm with a thickness of 10 cm, assuming only conduction? Value of thermal conductivity of the wall can be taken as 1 W/cm.K
- (a) 5000 W (b) 1000 W
(c) 7500 W (d) 3000 W




18. A mass of 1 kg of air at 27°C and 0.98 atm is taken through a diesel cycle. If the compression ratio of the engine is 16, calculate the temperature of the air after compression? (for calculation, take the ratio of specific heats of air as 1.5)
- (a) 1200 deg C
(b) 1473 deg C
(c) 927 deg C
(d) 768 deg C
19. An aircraft is in its take off roll at sea level with ambient temperature of 18°C . What is the approximate speed of the aircraft if the temperature measured by a probe at the exit of the engine diffuser is 36°C ? (Assuming air stagnation at diffuser outlet and C_p of air as 1.0 kJ/kg.K)
- (a) 12 m/s
(b) 3 m/s
(c) 6 m/s
(d) 18 m/s
20. The external surface of a wall of 3 m height, 5 m width and 0.5 m thickness is at a temperature of 2°C . If a heat loss of 150 W from the room is measured across the wall, find the inner wall temperature? The thermal conductivity of wall material can be taken as 1 W/m.K
- (a) 280 K
(b) 285 K
(c) 268 K
(d) 282 K
21. The typical range of Prandtl number for water is
- (a) 0.004-0.300
(b) 1.7 – 13.7
(c) 50-500
(d) 2000-1000
22. Analogy between momentum and heat transfer is known as
- (a) Stanton-Prandtl analogy
(b) Grassoff-Meyer analogy
(c) Chilton-Colburn analogy
(d) None of the above

	INDIAN SPACE RESEARCH ORGANISATION	SET A
	MECHANICAL	

23. Which of the following statement is true for a Rayleigh flow at $M=1$?
- Enthalpy is maximum
 - Entropy is maximum
 - Enthalpy is minimum
 - Both (b) and (c)
24. A fluid passes through a well insulated tube of 4.7 cm^2 cross section area and 5 m length. If the pipe friction coefficient is 0.07 and the flow velocity is 3 m/s , then the flow can be represented using?
- Rayleigh flow model
 - Isentropic flow model
 - Gino flow model
 - Fanno flow model
25. A fluid having a density of 1 g/cc is in a state with Grashof number 2×10^6 and prandtl number 0.7 . Assuming acceleration due to gravity as 10 m/s^2 , calculate the Rayleigh number?
- 1.4×10^6
 - 2.86×10^6
 - 3.7×10^5
 - 8.4×10^6
26. A cold liquid enters a counter flow heat exchanger at 15 deg at a rate of 8 kg/s . A hot stream of the same liquid enters the heat exchanger at 75 deg at 2 kg/s . Assuming the specific heat of the fluid as $4 \text{ kJ/kg} \cdot \text{C}$, determine the maximum heat transfer rate.
- 960 kW
 - 240 kW
 - 1920 kW
 - 480 kW
27. The temperature of a surface with 0.2 m^2 area is 17 deg C . Calculate the wavelength corresponding to maximum monochromatic emissive power
- 20 micrometers
 - 30 micrometers
 - 10 micrometers
 - 40 micrometers

	INDIAN SPACE RESEARCH ORGANISATION	SET A
	MECHANICAL	

28. For a surface, the direct and diffuse components of the solar radiation are 400 and 300 W/m² and the direct radiation makes 60 deg angle with the normal. If the surface temperature is 300 K and effective sky temperature is 200 K, calculate net rate of radiation heat transfer. (Assume solar absorptivity and emissivity as 0.1 each; For calculation Take Stefan Boltzmanns constant as $6 \times 10^{-8} \text{ W/m}^2.\text{K}^4$)
- (a) 11 W/m² (b) 45 W/m²
(c) 33 W/m² (d) 64 W/m²
29. Which of the following element is added to High Speed Tool Steels as a scavenger to remove slag impurities during melting and also for increasing cutting efficiency of tools.
- (a) Chromium (b) Vanadium
(c) Molybdenum (d) Manganese
30. Region of disorder created by movement of dislocations in superlattice is called:
- (a) Twin (b) Stacking fault
(c) Anti-phase boundary (d) Orowon loop
31. The state of stress during deep drawing forming operation of a cup is
- (a) In the flange of blank, uni-axial compression and in wall of cup, bi-axial tension and compression
(b) In the flange of the blank, uni-axial tension and in wall of cup, bi-axial tension and compression
(c) In the flange of the blank, bi-axial tension and compression and in the wall of cup, simple uni-axial tension
(d) Both flange and wall of the cup will have bi-axial compression and tension
32. During turning of a metallic rod at a given condition, the tool life was found to decrease from 100 min. to 25 min. when cutting speed was increased from 50 m/min. to 100 m/min. How much will be life of tool if machined at 80 m/min.?
- (a) 38.06 min. (b) 39.06 min.
(c) 40.06 min. (d) 41.06 min.

	INDIAN SPACE RESEARCH ORGANISATION	SET A
	MECHANICAL	

33. In a single pass rolling operation, the thickness of a 100 mm wide plate is reduced from 20mm to 15 mm. The roller radius is 125 mm and rotational speed is 8 rpm. The average flow stress for the plate material is 400 MPa. The power required for rolling operation in kW is?
- (a) $12.5 \pi / 3$ (b) 10π
(c) $40 \pi / 3$ (d) $20 \pi / 3$
34. A dummy activity is used in PERT network to describe
- (a) Precedence relationship (b) Necessary time delay
(c) Resource restriction (d) Resource idleness
35. In small castings, which of the following allowances can be ignored.
- (a) Shrinkage Allowance (b) Rapping Allowance
(c) Draft Allowance (d) Machining Allowance
36. In an arc welding process, two weld coupons were made using two different welding processes. For the first coupon, the voltage, current and welding speed used are 15 V, 300 A and 30 mm/min respectively. Whereas the second coupon is welded with 60 kV, 200 mA and 25 mm/s. If the heat transfer efficiency for welding the first coupon is half of that of second coupon, the ratio of heat input per unit length is?
- (a) 50:2 (b) 75:8
(c) 5:8 (d) 5:2
37. In Gas tungsten arc welding (GTAW) which of the following polarity is generally used for getting higher penetration
- (a) Direct current straight polarity (DCSP)
(b) Direct current reverse polarity (DCRP)
(c) Alternating Current high frequency (ACHF)
(d) All of the above

38. The laws of adhesive wear, commonly referred to as Archard's law can be expressed as _____.
- (If 'Q' is the total volume of wear debris produced, 'W' is the normal load, 'L' is the sliding distance, 'H' is the hardness of the softest contacting surfaces being worn away, and 'k' is a non-dimensional wear coefficient dependent on the materials in contact and their exact degree of cleanliness)
- (a) $Q = kWL/H$ (b) $Q = kW/LH$
(c) $Q = kHW/L$ (d) $Q = k/LWH$
39. In a four-bar linkage if 'S' is the length of the shortest link, 'L' is the length of longest link and 'P' & 'Q' are length of other links, then the criteria for getting a triple rocker mechanism in which no links will fully rotate is.
- (a) $S + Q > P + L$ (b) $S + L < P + Q$
(c) $S + L = P + Q$ (d) $S + L > P + Q$
40. The piston of an engine moves with simple harmonic motion. The crank rotates at 120 r.p.m. with a stroke of 2 meters. The velocity of the piston, when it is at a distance of 0.8 metre from the center is.
- (a) 4.8π (b) 2.4π
(c) 1.2π (d) 0.6π
41. If a block slides outward on a link at a uniform rate of 30 m/s, while the link is rotating at a constant angular velocity of 50 rad/s counter clockwise, the Coriolis component of acceleration is _____ m/s².
- (a) 1000 (b) 1500
(c) 3000 (d) 4500
42. In a screw jack of lead angle α , the effort required to lift the load W is given by _____
(ϕ = Friction Angle)
- (a) $P = W \tan(\alpha - \phi)$ (b) $P = W \tan(\alpha + \phi)$
(c) $P = W \cos(\alpha - \phi)$ (d) $P = W \cos(\alpha + \phi)$



INDIAN SPACE RESEARCH ORGANISATION

MECHANICAL

SET
A

43. When the axes of first and last gear are co-axial, then gear train is known as
(a) simple gear train (b) compound gear train
(c) reverted gear train (d) epicyclic gear train
44. A disc spinning on its axis at 20 rad/s will undergo precession when a torque 100 N-m is applied about an axis normal to it. If the mass moment of inertia is 1 kg-m², then the angular velocity of precession is?
(a) 0.2 rad/s (b) 5 rad/s
(c) 10 rad/s (d) 200 rad/s
45. Which of the following is an absorption type dynamometer?
(a) Prony brake dynamometer (b) Epicyclic-train dynamometer
(c) Torsion dynamometer (d) Belt transmission dynamometer
46. Which of the following mechanism provides intermittent rotary motion?
(a) Chebyshev linkage (b) Geneva Mechanism
(c) Peaucellier Mechanism (d) Roberts Mechanism
47. If m, n are integers and $m + n$ is odd then the value of $\int_0^{\pi} \sin mx \cdot \cos nx \cdot dx$ is
(a) 0 (b) $\pi/2$
(c) π (d) 1
48. $1 + x + x^2/2 - x^4/8 - x^5/15 + \dots =$
(a) $e^{\tan x}$ (b) $e^{\cos x}$
(c) $e^{\sin x}$ (d) $e^x \sin x$



49. The Laplace transform of $e^{at} \cos \omega t$

(a) $\frac{(s-a)}{(s-a)^2 + \omega^2}$

(b) $\frac{\omega}{(s-a)^2 + \omega^2}$

(c) $\frac{a}{(s-a)^2 + \omega^2}$

(d) $\frac{S}{(s-a)^2 + \omega^2}$

50. If $v = yzi + 3zxj + zk$, then curl v is

(a) $-3xi + yj + 2zk$

(b) $3xi - yj + 2zk$

(c) $-3xi - yj - 2zk$

(d) $3xi + yj - 2zk$

51. $\cos(z)$ can be expressed as

(a) $\frac{1}{2}(e^{iz} + e^{-iz})$

(b) $\frac{1}{2}(e^{iz} - e^{-iz})$

(c) $\frac{1}{2i}(e^{iz} + e^{-iz})$

(d) $\frac{1}{2i}(e^{iz} - e^{-iz})$

52. In a vector field, Divergence of the gradient is

(a) curl

(b) unity

(c) zero

(d) Laplacian

53. If a continuously differentiable vector function is the gradient of a scalar function, then its curl is


(a) infinite

(b) indeterminate

(c) unity


(d) zero

54. What does 'a' and 'e' indicate in the surface texture symbol shown below




- (a) Roughness value, machining allowance
- (b) Production method, roughness value
- (c) Machining allowance, sampling length
- (d) Heat treatment method, sample length

55. Two steel trusses, XY and YZ of identical size supports a load of 200 N as shown in fig. The length of the truss is 1m. The force in the truss xy in N is



- (a) 100 N
- (b) 200 N
- (c) 150 N
- (d) 50 N

56. A block weighing 100 N is resting on a plane inclined with horizontal as shown in Fig. What horizontal force P is necessary to hold the body from sliding down the plane? (Coefficient of friction can be taken as 0.25)




- (a) 30 N
- (b) 120 N
- (c) 60 N
- (d) 15 N




57. The ratio of maximum shear stress to average shear stress in a beam of rectangular section is
- (a) 5.1 (b) $2/3$
(c) $3/2$ (d) 1.0

58. A massless beam has a loading pattern shown in figure. Find the bending moment at mid span?



- (a) 1 kN-m (b) 3 kN-m
(c) 2 kN-m (d) 0.0 kN-m
59. Steel machine element at the critical section is in biaxial stress state with two principal stress being 300 N/mm^2 and 300 N/mm^2 (equal magnitude). Find the von Mises stress (in N/mm^2) in the member
- (a) 212.1 (b) 600
(c) 424.2 (d) 300
60. A machine component of 90 kg mass needs to be held in position using three springs as shown below. The spring constants K_1 , K_2 and K_3 are 4, 4 and 8 N/m respectively. Find the natural frequency of the system in rad/sec.



- (a) 0.33 (b) 0.42
(c) 0.13 (d) 3.0

71. Which of the following hardness tester uses Diamond cone type indenter?
- (a) Brinell (b) Vickers
(c) Knoop (d) Rockwell
72. In a two component system, if the non-compositional variable is only temperature, the number of degrees of freedom in the case of a single phase field as per Gibbs Phase Rule is?
- (a) 0 (b) 1
(c) 2 (d) 3
73. In an iron – carbon diagram, the percentage by weight of carbon at eutectoid composition is
- (a) 1.12 (b) 0.76
(c) 0.24 (d) 0.03
74. Of the various microstructures that may be produced for a given steel alloy, which among the following is the hardest form
- (a) Martensite (b) Pearlite
(c) Bainite (d) Spheroidite
75. Which spring steel is widely used for aircraft engine valves
- (a) Oil tempered wire (0.6 C to 0.7C)
(b) Chrome vanadium
(c) Hard drawn wire (0.6 C to 0.7C)
(d) Phosphor bronze wire



76. If, K_f is the fatigue stress concentration factor and K_t is the theoretical stress concentration factor then, the notch sensitivity q is?
- (a) $(K_f + 1)/(K_t + 1)$ (b) $(K_f - 1)/(K_t - 1)$
(c) $(K_t - 1)/(K_f - 1)$ (d) $(K_f - 1)/(K_t + 1)$
77. Beach or clamshell marks on a failed metallic surface are typical of
- (a) Ductile fracture (b) Brittle fracture
(c) Creep failure (d) Fatigue failure
78. In vibration isolation if ω / ω_n is less than $\sqrt{2}$ then the transmissibility will be
- (a) Less than one (b) Equal to one
(c) Greater than one (d) Zero
79. The natural frequency of a simply supported beam of length l with mass M at its centre, flexural rigidity EI and negligible beam mass is
- (a) $\frac{1}{2\pi} \sqrt{\frac{48EI}{Ml^3}}$ (b) $\frac{1}{2\pi} \sqrt{\frac{3EI}{Ml^3}}$
(c) $\frac{1}{2\pi} \sqrt{\frac{EI}{Ml^3}}$ (d) None of the above
80. A machine component of natural frequency 20 rad/s is subjected to a base motion from the machine which is harmonic in nature with amplitude 3 m/s^2 at 10 rad/s. What is the peak amplitude of relative displacement of the components if the damping is negligible?
- (a) 0.1mm (b) 1.0 mm
(c) 10.0 mm (d) 100.0 mm